

# EMC 2015

## IMPULSE GENERATOR - SYSTEM

### Highlights:

- Plug-in system
- Different wave forms
- Compact
- Portable
- EMI-SIMULATOR

The impulse generator system EMC 2015 has been designed for dielectric testing of electric components, over-voltage protectors and electronic circuits acc. IEC, VDE etc. The basic version generates impulse currents with waveform 8/20 µs and a peak value up to 25 kA.

In addition, various other plug-ins are also available.



PFN plug-in's	Peak value	Wave form
<b>Impulse current</b>	<b>25 kA</b>	<b>8 / 20 µs</b>
	<b>5 kA</b>	<b>10 / 50 µs</b>
	<b>600 A</b>	<b>10 / 350 µs</b>
	<b>300 A</b>	<b>10 / 700 µs</b>
	<b>200 A</b>	<b>10/1000 µs</b>
<b>Impulse voltage</b>	<b>10 kV</b>	<b>10 / 700 µs</b>
<b>Combination wave</b>	<b>2 * 10 kV</b>	<b>1.2 / 50 µs</b>
		<b>8 / 20 µs</b>

Dependent upon type, pulse forming plug-ins contain high pulse-fidelity current viewing resistors, or voltage dividers, for measurement of the output parameters. The impulse output is located on the top of the equipment and provides high-current connectors for a plug-in test adapter.

The EMC 2015 features a microprocessor controlled user interface and 7" touch screen display unit for ease of use. The microprocessor allows the user to either execute standard test routines, or a 'user defined' test sequence. A standard USB port provides the ability to print a summary of the test parameters to a USB stick.

The software program EMC-REMOTE allows full remote control of the test generator via Ethernet light guide as well as documentation and evaluation of test results, accordingly to the IEC 17025. To record definite impulses with an oscilloscope, it is equipped with an Impulse Recording Function (IRF).

Option	EMC 2015
<b>Software EMC-REMOTE Test, for remote control</b>	
With Impulse Recording Function (IRF)	
( XP, WIN7, WIN10 ) incl. 5 m fibre optic cable and PC Ethernet interface	

TECHNICAL SPECIFICATIONS	EMC 2015
<b>Mainframe</b>	
Microprocessor controlled touch panel	7", capacitive
Optical Ethernet Interface for remote control of the generator	optional
Interface for saving reports	USB
External trigger input / output	Switch/ 10 V
Peak value of charging voltage, adjustable,	0.2 - 10 kV ± 2 %
Output pulse polarity, switch able	POS/NEG/ALT
max. stored energy	1500 J
Energy storage capacitor, standard version	30 µF / 10 kV
Charging time	<20s
Waveform and amplitude of the pulse output according to the selected plug-in	
Connector for external safety interlock loop and external red and green warning lamps acc. to VDE 0104	24 V = 24 V=, 40 mA
Mains power	230 V , 50/60 Hz
Dimensions: desk top case W * H * D	556*470*600 mm <sup>3</sup>
Weight	65kg
<b>Safety test cover:</b>	
mounted on the top of the equipment, safety interlock loop connected to the limit switch, red and green warning lamps installed	
Dimensions: W * H * D	ca. 440*180*300 mm <sup>3</sup>

Available waveform plug-in's, Part 1	EMC 2015
<b>Impulse current plug-in: basic configuration</b>	<b>8 / 20 µs, 25 kA</b>
Impulse output current, adjustable via charging voltage	2 - 25 kA ± 5 %
Waveform of impulse output current, acc. to IEC 60060	8 / 20 µs ±20 %
Ringing	< 30 %
Current viewing resistor, built-in	1 mΩ, 20 MHz
<b>Impulse current plug-in:</b>	<b>10 / 50 µs, 5.0 kA</b>
Impulse output current, adjustable via charging voltage	0.2 - 5.0 kA ± 5 %
Waveform of impulse output current, acc. to IEC 60060	10 / 50 µs ±20 %
Ringing	< 30 %
Current viewing resistor, built-in	1 mΩ, 20 MHz
<b>Impulse current plug-in:</b>	<b>10 / 350 µs, 600 A</b>
Impulse output current, adjustable via charging voltage	50 - 600 A ± 5 %
Waveform of impulse output current, acc. to IEC 60060	10 / 350 µs ±20 %
Ringing	< 30 %
Current viewing resistor, built-in	10 mΩ, 20 MHz
<b>Impulse current plug-in:</b>	<b>10 / 700 µs, 300 A</b>
Impulse output current, adjustable via charging voltage	20 - 300 A ± 5 %
Waveform of impulse output current, acc. to IEC 60060	10 / 700 µs ±20 %
Ringing	< 30 %
Current viewing resistor, built-in	20 mΩ, 20 MHz
<b>Impulse current plug-in:</b>	<b>10 / 1000 µs, 200 A</b>
Impulse output current, adjustable via charging voltage	10 - 200 A ± 5 %
Waveform of impulse output current, acc. to IEC 60060	10 / 1000 µs ±20 %
Ringing	< 30 %
Current viewing resistor, built-in	20 mΩ, 20 MHz
<b>Impulse voltage plug-in: special version</b>	<b>10 / 700 µs, 10 kV</b>
Energy storage capacitor, special version!!	20 µF / 10 kV
Impulse output voltage, adjustable via charging voltage	1.0 - 10 kV ± 5 %
Waveform acc. to IEC 60060, CCITT K17/K22	10 / 700 µs ±20 %
Impulse voltage divider, built-in	ratio 1000:1±2%, 10 MHz

Available waveform plug-in's, Part 2	EMC 2015
<b>Combination wave plug-in:</b> acc. to VDE 0845-2, designed for testing two gap over-voltage protectors	8 / 20 $\mu$ s, 25 kA / 1.2 / 50 $\mu$ s, 10kV
Impulse output current, adjustable via charging voltage	2 * 1 - 10 kA $\pm$ 5 %
Waveform of impulse output current, acc. to IEC 60060	8 / 20 $\mu$ s $\pm$ 20 %
Ringing	< 30 %
Current viewing resistor, built-in	1.0 mΩ, 20 MHz
Impulse output voltage, adjustable via charging voltage	10 kV $\pm$ 5 %
Waveform of impulse output voltage, acc. to IEC 60060	1.2 / 50 $\mu$ s $\pm$ 30 %/ $\pm$ 20 %
Impulse voltage divider, built-in	ratio 1000:1 $\pm$ 2 %, 10 MHz
<b>Wave form plug-in for testing varistors:</b>	
<b>Impulse current plug-in:</b>	8 / 20 $\mu$ s, 2.5 kA
Impulse output current, adjustable via charging voltage	0.2 - 2.5 kA $\pm$ 5 %
Waveform of impulse output current, acc. to IEC 60060	8 / 20 $\mu$ s $\pm$ 20 %
Ringing	< 30 %
Current viewing resistor, built-in	20 mΩ, 20 MHz